

BR33

Wireless Panic Button



Whether it's an armed intruder or medical emergency, situations that require immediate action can crop up anytime, anywhere. Verkada's panic button enables you to immediately call for help, while leveraging other Verkada devices to provide additional context about an incident.

Completely customizable

- Choose from single, double, triple, or long press to reduce false alarms
- Pair with nearby cameras to immediately see what's going on in the vicinity
- Can be worn on a lanyard or mounted on a wall or desk

Natively integrates with Verkada ecosystem

- Decide who will be notified and whether emergency services should be contacted directly
- Buttons can trigger a door lockdown, turn on an alarm signaling device and more
- Digital panic button available on Alarms mobile app

Easy to set up

- Wireless panic buttons pair automatically with the Wireless Hub, Alarm Console, or Alarm Keypad + Hub
- Easily set up and manage settings in the Command cloud dashboard, even on-the-go

Built to last

- Get notified if a panic button goes offline or reports low battery
- Up to 5 year battery life
- 10-year warranty
- Automatic firmware updates keep systems secure



BR33 Wireless Panic Button

Tech Specs

**BR33**

Power and network

Power Supply	1 x CR123A lithium battery	Wireless Communication	Proprietary 915 MHz (US, Canada) / 868 MHz (UK, Europe) / 916.8 MHz (ANZ)
Battery Life	Up to 5 years	Connectivity	Connects to the BC82 Alarm Console, BK21 Alarm Keypad, or BH61 Wireless Hub

Sensor features

Wireless Range	305m / 1,000ft (line-of-sight) 61m / 200ft (typical environment)	Button Press Options	Single, double, triple, press-and-hold
-----------------------	---	-----------------------------	--

General

Dimensions	Height: 81mm / 3.2in Width: 36mm / 1.42in Depth: 124mm / 0.94in	Operating Temperature	0°C to 45°C / 32°F to 113°F; 0-90% humidity
Weight	49g / 1.73oz	LED Indicator	Successful transmission, unsuccessful transmission, low battery
Certifications	FCC, IC, CE, UKCA, RCM, IFETEL, NDAA, EN 50131 (Grade 2)	Warranty	10 years

Installation

Included Accessories	QSG, wall screws, wall anchors, torx wrench, VHB adhesive mount	Mounting Options	Wall or surface mount; loop for lanyard attachment
-----------------------------	---	-------------------------	--



Ordering Information

BR33 Wireless Panic Button pricing

Model Number	Description	Cost (MSRP) USD
BR33-HW	Wireless Panic Button	\$99

LIC-BB Basic Alarm License pricing*

Includes alarm monitoring with no video verification

LIC-BB-1Y	1-Year Basic Alarm License	\$600
LIC-BB-3Y	3-Year Basic Alarm License	\$1,800
LIC-BB-5Y	5-Year Basic Alarm License	\$3,000
LIC-BB-10Y	10-Year Basic Alarm License	\$6,000

LIC-BA Standard Alarm License pricing*

Includes professional monitoring with video verification, up to 100 events/month

LIC-BA-1Y	1-Year Standard Alarm License	\$1,500
LIC-BA-3Y	3-Year Standard Alarm License	\$4,500
LIC-BA-5Y	5-Year Standard Alarm License	\$7,500
LIC-BA-10Y	10-Year Standard Alarm License	\$15,000

LIC-BV Premium Alarm License pricing*

Includes professional monitoring with video verification, up to 1,000 events/month

LIC-BV-1Y	1-Year Premium Alarm License	\$12,000
LIC-BV-3Y	3-Year Premium Alarm License	\$36,000
LIC-BV-5Y	5-Year Premium Alarm License	\$60,000
LIC-BV-10Y	10-Year Premium Alarm License	\$120,000

*One Alarm License needed per physical address; required to operate all Verkada Alarms hardware.